



LED Astro



Питание:AC100-240W 50-60HZ

Энергопотребление: 120W

**Источник света: 12 *10W RGBW 4in1 LED lamp
beads+ Laser(red laser:100MW, green
laser:50MW)**

**Режимы управления: DMX512, авто, звук,
режим ведущий-ведомый.**

DMXканалы: 11, 14.

Материал корпуса: алюминий и пластик.

Вращение: 540 °, 630 °, бесконечноевращение

**Режимывращения: ось X – программируемое
вращение, ось Y – бесконечное вращение.**

Диммирование:0-100%.

**Система охлаждения:принудительное
охлаждение с помощью вентилятора.**

**Применимые условия: бар, караоке, мини-шоу
и т.д.**

Product size:220*170*310 (mm)

				MANU	PAN, TILT RED, GREEN, BLUE, WHITE, DIMMER, STROBE,
ADDR	A001---A512	CHND	1	TEST	Automatic test
1CH, 14CH				VER	V104 Software version number
SLND	MAST, SLAV			RSET	YES,NO factory data reset
SHND	SOUND, AUTO (SPEED SP0—SP9)				
SENS	Sound control sensitivity (0 off, 100 most sensitive)				
BLND	YES, NO	Standby mode			
LED	ON, OFF	Background light switch			
DISP	YES, NO	The reverse shows			
PAN	YES, NO	Horizontal motor reversal			
TILT	YES, NO	Vertical motor reversal			

14 channel mode

Channel	Function	Instruction
1	Horizontal operation	0-255
2	Vertical (1) operation	0-255
3	Vertical (2) operation	0-255
4	Horizontal vertical speed	0-255
5	Dimming	0-255
6	Strobe	0-255
7	Red dimming	0-255
8	Green dimming	0-255
9	Blue dimming	0-255
10	White dimming	0-255
11	Color Auto	0-255
12	Moto Auto	0-255
13	Auto speed	0-255
14	Reset	250-255 (5 seconds)

11 channel mode

Channel	Function	Instruction
1	Horizontal operation	0-255
2	Vertical (1) operation	0-255
3	Vertical (2) operation	0-255
4	Horizontal vertical speed	0-255
5	Dimming	0-255
6	Strobe	0-255
7	Red dimming	0-255
8	Green dimming	0-255
9	Blue dimming	0-255
10	White dimming	0-255
11	Reset	250-255 (5 seconds)