



LED Kaleidoscope



### Технические характеристики

1. Рабочее напряжение: AC95V-245V 50-60Hz
2. Мощность: 50 Вт (волшебный шар 15 Вт, фиолетовый свет 12 Вт, стробоскоп 20 Вт, красный и зеленый лазер 30 мВт)
3. Параметры светодиодов: 4 шт. фиолетовых светодиода 3 Вт, 1 шт. светодиод OSRAM 4-в-1 15 Вт, 2 шт. стробоскопических светодиода 10 Вт, красно-зеленый лазер 30 мВт
4. Режим управления: Международный DMX 512, 14 каналов
5. Режим работы: DMX512, ведущий/ведомый, автоматическое перемещение, голосовое управление
6. Режим затемнения: 0~100% сверхплавное затемнение
7. Частота стробоскопа: 20 раз в секунду

### 2. Рабочие функции

display	function
A001-A512	Control desk/ slavemode
A1 1-A1 9	RedLED, the higher the fourth digit, the faster the rotation speed.
A2 1-A2 9	Green LED, the higher the fourth digit, the faster the rotation speed.
A3 1-A3 9	BlueLED, the higher the fourth digit, the faster the rotation speed.
A4 1-A4 9	White LED, the higher the fourth digit, the faster the rotation speed.
A5 1-A5 9	UVLED, the higher the fourth digit, the faster the rotation speed.
A6 1-A6 9	Laser, the higher the fourth digit, the brighter the laser.
A7 1-A7 9	Strobe, the higher the fourth digit, the faster the stroboscopes speed.
A8 1-A8 9	autorun, the higher the fourth digit, the faster the self-propelled speed is.
S1 1-S1 9	Voice 1, the higher the fourth digit value, the higher the sensitivity.
S2 1-S2 9	Voice 2, the higher the fourth digit value, the higher the sensitivity.

### 3. Описание функций

14 chann el	fucntion	DMXvalue	description
1	Magicmotor	0-255	0-127 rotationposition 0-340 degrees, 128-255 motor self-rotationfromfasttoslow
2	Rotation amplitude	0-255	Controlmotorself-movingrange 0-255 (0-340 degrees) channellismorethan 128 effective
3	Lasermotor	0-255	0~9(stop10~255 fromslowtofast
4	Dimmer	0-255	Lineardimmingfromdarktolight
5	Strobe Rdimmer	0-9	None
		10-255	Strobefromslowtofast
		0-255	RedLEDfromdarktobright
6		0-255	RedLEDfromdarktobright
7	Gdimmer	0-255	GreenLEDfromdarktobright
8	Bdimmer	0-255	BlueLEDfromdarktobright
9	Wdimmer	0-255	WhiteLEDtonesfromdarktobright
10	Purpledimming Rlaserdimmer	0-255	Purpledimmingfromdarktobright
11		0-255	Redlaserfromdarktobright
12	Glaserdimmer	0-255	Greenlaserfromdarktobright
13	WStrobe	0-255	Strobefromslowtofast
14	Macrofunction control	0-50	Channel 1 tochannel 13 isvalid
		51-150	Autorun
		150-255	Voice

4	LED white light
5	UV purple light
6	Laser pattern
7	White light flash
8	Self-walking mode
9	Voice Model
0	Voice Mode2

#### 4. Беспроводное управление

ON	The lights open
OFF	The lights are closed
DMX	DMX Mode
AUTO	AutoMode Select
speed+	AutoMode Speed Up
speed-	AutoMode Speed Down
voice	S1-S2 Voice Mode
mic+	Voice Sensitivity Up
mic-	Voice Sensitivity Down
1	LED glow
2	LED Green Flash
3	LED blue ligh

